

SPECIFICATION

ANTIFERROELECTRIC LIQUID CRYSTAL DISPLAY AND METHOD
OF DRIVING THE SAME

5

TECHNICAL FIELD

The present invention relates to an antiferroelectric liquid crystal display, such as a liquid crystal display panel or a liquid crystal optical shutter array, having a liquid crystal layer of antiferroelectric liquid crystal, and a method of driving the same.

BACKGROUND ART

15 Liquid crystal panels using antiferroelectric liquid crystals have been researched extensively since it was reported in Japanese Patent Unexamined Publication No. 2-173724 by Nippondenso and Showa Shell Sekiyu that such liquid crystal panels provide wide viewing angles, are capable of fast response, and have good multiplexing characteristics.

20 The conventional art driving method, however, has had the problem that after the same image pattern has been displayed for a long period of time, when a different image pattern is displayed on the screen, the previously displayed image remains slightly visible on the screen (this phenomenon is hereinafter called the "image sticking phenomenon").

25 It is believed that this phenomenon occurs because an antiferroelectric liquid crystal cell is formed in a layer structure and the amount of light transmitted through the liquid crystal panel varies depending on the geometry of the layer structure. To prevent this image sticking phenomenon, it has been proposed to apply a layer structure controlling voltage waveform each time the layer structure changes. For example, Japanese Patent Unexamined Publication No. 6-202078 discloses a

configuration in which, in addition to the usual display driving circuit, a layer structure controlling voltage waveform circuit is provided which applies a layer structure controlling voltage waveform to the liquid crystal panel.

However, since the layer structure controlling voltage waveform differs in frequency and peak value from the display driving voltage waveform, the layer structure controlling voltage waveform circuit, including a clock generating circuit, voltage value conversion circuit, etc., needs to be provided separately from the display driving circuit. As a result, two circuits, i.e., the display driving circuit and the layer structure controlling voltage waveform circuit, must be provided for one liquid crystal display, which not only increases the size and complexity of the liquid crystal display circuitry but also leads to higher manufacturing costs.

It is, accordingly, an object of the present invention to provide an antiferroelectric liquid crystal display that is compact in construction and inexpensive to manufacture by using a display driving circuit adapted to output a layer structure controlling voltage waveform and thereby eliminating the need to provide a layer structure controlling voltage waveform circuit separately. It is also an object of the present invention to provide a method of driving such an antiferroelectric liquid crystal display.

DISCLOSURE OF THE INVENTION

After studying the display driving voltage waveform and layer structure controlling voltage waveform for antiferroelectric liquid crystal, it has been discovered that if the display driving voltage waveform is set so that the peak value of the scanning voltage applied during the non-selection period becomes equal to the peak value of the voltage applied during the selection period, a voltage waveform close to the optimum layer structure

controlling voltage waveform can be obtained.

In view of this, to achieve the above object, in the present invention, the display driving voltage waveform is set so that the peak value of the scanning voltage waveform applied during the selection period becomes equal to the peak value of the scanning voltage waveform applied during the non-selection period, and the thus set display driving voltage waveform is output as a layer structure controlling voltage waveform, not as a display driving voltage waveform, from the display driving circuit for a predetermined length of time for application to the liquid crystal.

Further, the liquid crystal panel includes a temperature sensor and, in accordance with the information output from the temperature sensor, the display driving voltage waveform in which the peak value of the scanning voltage waveform applied during the selection period is set equal to the peak value of the scanning voltage waveform applied during the non-selection period is output as the layer structure controlling voltage waveform for the predetermined length of time.

Alternatively, the display driving voltage waveform with both peak values set equal is output as the layer structure controlling voltage waveform for predetermined length of time at predetermined intervals of time.

Preferably, the display driving voltage waveform has a reset period preceding the selection period.

ADVANTAGEOUS EFFECT OF THE INVENTION

According to the present invention, in the display driving voltage waveform, the peak value of the voltage waveform applied during the selection period is set equal to the peak value of the voltage waveform applied during the non-selection period. By using this waveform as the layer structure controlling voltage waveform, it becomes possible to reduce the "image sticking phenomenon"

Furthermore, since the temperature sensor is provided so that the layer structure controlling voltage waveform is applied at appropriate timing, the "image sticking phenomenon" can be reduced in a reliable manner.

BRIEF DESCRIPTION OF THE DRAWINGS

Figure 1 is a diagram showing the arrangement of a liquid crystal device when antiferroelectric liquid crystal is used as a display.

Figure 2 is a diagram showing how the light transmittance of the antiferroelectric liquid crystal display device varies with an applied voltage.

Figure 3 is a diagram showing driving voltage waveforms for antiferroelectric liquid crystal according to the conventional art, and their corresponding light transmittance.

Figure 4 is a diagram showing the layer structure within an antiferroelectric liquid crystal cell.

Figure 5 is a graph showing an example of the relationship between the layer spacing and the temperature of the antiferroelectric liquid crystal.

Figure 6 is a diagram showing an example of the variation of light transmittance with temperature history of the antiferroelectric liquid crystal.

Figure 7 is a diagram showing an example of a layer structure controlling voltage waveform.

Figure 8 is a diagram showing a waveform when the display driving voltage waveform for antiferroelectric liquid crystal shown in Figure 3 is set so that the peak value of the scanning voltage applied during the non-selection period becomes equal to the peak value of the

~~voltage applied during the selection period.~~

Figure 9 is a diagram showing a waveform when the reset period is set to 0 in the waveform shown in Figure 8.

5 Figure 10 is a block diagram of the antiferroelectric liquid crystal display according to the present invention.

Figure 11 is a diagram showing an example of the configuration of a power supply circuit in Figure 10.

10 Figure 12 is a diagram showing the voltage waveform applied to the liquid crystal in the antiferroelectric liquid crystal display of the present invention.

15 Figure 13 is a diagram showing an example of the structure of the antiferroelectric liquid crystal panel used in the present invention.

DETAILED DESCRIPTION OF THE INVENTION

20 Embodiments of the present invention will be described in detail below with reference to the accompanying drawings.

25 Figure 1 is a diagram showing the arrangement of a liquid crystal device, when an antiferroelectric liquid crystal is used, as a display. Between polarizers 1a and 1b arranged in a crossed Nicol configuration is placed a liquid crystal cell 2 in such a manner that the average long axis direction X of molecules in the absence of an applied voltage is oriented substantially parallel to either the polarization axis, a, of the polarizer 1a or the polarization axis, b, of the polarizer 1b. Then, the liquid crystal cell is set up so that a black display is produced when no voltage is applied and a white display produced when a voltage is applied.

30 When the voltage is applied across the thus arranged liquid crystal device, its light transmittance varies with the applied voltage, describing a loop as plotted in the graph of Figure 2. The voltage value at which the light transmittance begins to change when the applied

voltage is increased is denoted by V1, and the voltage value at which the light transmittance reaches saturation is denoted by V2, while the voltage value at which the light transmittance begins to drop when the applied
5 voltage is decreased is denoted by V5. Further, when a voltage of opposite polarity is applied, the voltage value at which the light transmittance begins to change when the absolute value of the applied voltage is increased is denoted by V3, and the voltage value at
10 which the light transmittance reaches saturation is denoted by V4, while the voltage value at which the light transmittance begins to change when the absolute value of the applied voltage is decreased is denoted by V6. As shown in Figure 2, a first ferroelectric state is
15 selected when the value of the applied voltage is greater than the threshold of the antiferroelectric liquid crystal molecules. When the voltage of opposite polarity greater than the threshold of the antiferroelectric liquid crystal molecules is applied, a second
20 ferroelectric state is selected. In either of these ferroelectric states, when the voltage value drops below a certain threshold, an antiferroelectric state is selected. The antiferroelectric liquid crystal display can be constructed to produce a black display in the
25 antiferroelectric state or a white display in the antiferroelectric state. The present invention is applicable to both modes of operation. However, the description hereinafter given assumes that the display is set up to produce a black display in the
30 antiferroelectric state.

Sub
a4
4

Figure 3 is a diagram showing display driving voltage waveforms for an antiferroelectric liquid crystal according to the conventional art. As shown in Figure 3, writing to a pixel is accomplished by applying a scanning voltage (a) to a scanning electrode and a signal voltage (b) to a signal electrode and thereby applying the resulting composite voltage (c) to the pixel which is

formed from a liquid crystal element. According to the conventional art, when driving an antiferroelectric liquid crystal display, the first or second ferroelectric state or the antiferroelectric state is selected in a selection period (Se), and the selected state is held throughout the following non-selection period (NSe), as shown in Figure 3. That is, a selection pulse is applied in the selection period (Se), and the light transmittance (d) obtained as the result of the selection is maintained throughout the following non-selection period (NSe) to produce the display.

In an antiferroelectric liquid crystal display device, it is generally practiced to reset the antiferroelectric liquid crystal to the first or second ferroelectric state or the antiferroelectric state immediately before writing to the pixel. For example, in Figure 3, each selection period (Se) is immediately preceded by a reset period (Rs). During this reset period, a voltage lower than the threshold voltage is applied to the pixel to reset the antiferroelectric liquid crystal to the antiferroelectric state. By resetting the state of each pixel in this way immediately before writing necessary information to the pixel, a good display can be produced with each pixel being unaffected by its previously written state.

In Figure 3, F1, F2, F3, and F4 denote the first, second, third, and fourth frames, respectively. In this waveform diagram, a white display is produced in the first and second frames, and a black display is produced in the third and fourth frames. The voltage polarity is usually reversed from one frame to the next, as shown in the figure.

Antiferroelectric liquid crystal used in an antiferroelectric liquid crystal display forms a layer structure with layers called smectic layers within a liquid crystal panel. The geometry of this layer structure changes according to the applied voltage

5 waveform, as shown in Figure 4.

Sub 25 #

5 Figure 4 is a diagram showing the layer structure formed within the antiferroelectric liquid crystal cell; as shown, a liquid crystal layer 20 is sandwiched between a pair of glass substrates 21a and 21b. Immediately after the liquid crystal is injected into the liquid crystal panel, the layer structure is the chevron structure with the layers bent in the middle between the top and bottom glass substrates, as shown part (a) of the figure. When the layer structure controlling voltage waveform is applied, the layer structure changes to the bookshelf structure with the layers lying perpendicular to the top and bottom substrates, as shown in part (b) of the figure. If the temperature changes thereafter, causing a change in the smectic layer spacing, the layer structure changes to a structure similar to the initial chevron structure, as shown in part (c) of the figure. Thereafter, when the display voltage waveform is applied to the liquid crystal cell, the layer structure changes to a quasi-bookshelf structure in the case of a white display, while in the case of a black display, the layer structure remains substantially unchanged and the layer structure shown in part (c) is retained.

15 The earlier described "image sticking phenomenon" is believed to be caused by the layer structure differing in a manner dependent on the temperature change and display state.

25 Next, a description will be given of the relationships of the layer spacing and light transmittance relative to the temperature of the liquid crystal layer.

30 Figure 5 shows an example of the relationship between the layer spacing and the temperature of antiferroelectric liquid crystal. In the case of the liquid crystal shown in the figure, the layer spacing dR is the smallest at room temperature T_R , the layer spacing increasing as the temperature drops below T_R , as shown,

35

	1980	1981	1982	1983	1984	1985	1986	1987	1988	1989	1990	1991	1992	1993	1994	1995	1996	1997	1998	1999	2000	2001	2002	2003	2004	2005	2006	2007	2008	2009	2010	2011	2012	2013	2014	2015	2016	2017	2018	2019	2020	2021	2022	2023	2024	2025	2026	2027	2028	2029	2030	2031	2032	2033	2034	2035	2036	2037	2038	2039	2040	2041	2042	2043	2044	2045	2046	2047	2048	2049	2050	2051	2052	2053	2054	2055	2056	2057	2058	2059	2060	2061	2062	2063	2064	2065	2066	2067	2068	2069	2070	2071	2072	2073	2074	2075	2076	2077	2078	2079	2080	2081	2082	2083	2084	2085	2086	2087	2088	2089	2090	2091	2092	2093	2094	2095	2096	2097	2098	2099	2100	2101	2102	2103	2104	2105	2106	2107	2108	2109	2110	2111	2112	2113	2114	2115	2116	2117	2118	2119	2120	2121	2122	2123	2124	2125	2126	2127	2128	2129	2130	2131	2132	2133	2134	2135	2136	2137	2138	2139	2140	2141	2142	2143	2144	2145	2146	2147	2148	2149	2150	2151	2152	2153	2154	2155	2156	2157	2158	2159	2160	2161	2162	2163	2164	2165	2166	2167	2168	2169	2170	2171	2172	2173	2174	2175	2176	2177	2178	2179	2180	2181	2182	2183	2184	2185	2186	2187	2188	2189	2190	2191	2192	2193	2194	2195	2196	2197	2198	2199	2200	2201	2202	2203	2204	2205	2206	2207	2208	2209	2210	2211	2212	2213	2214	2215	2216	2217	2218	2219	2220	2221	2222	2223	2224	2225	2226	2227	2228	2229	2230	2231	2232	2233	2234	2235	2236	2237	2238	2239	2240	2241	2242	2243	2244	2245	2246	2247	2248	2249	2250	2251	2252	2253	2254	2255	2256	2257	2258	2259	2260	2261	2262	2263	2264	2265	2266	2267	2268	2269	2270	2271	2272	2273	2274	2275	2276	2277	2278	2279	2280	2281	2282	2283	2284	2285	2286	2287	2288	2289	2290	2291	2292	2293	2294	2295	2296	2297	2298	2299	2300	2301	2302	2303	2304	2305	2306	2307	2308	2309	2310	2311	2312	2313	2314	2315	2316	2317	2318	2319	2320	2321	2322	2323	2324	2325	2326	2327	2328	2329	2330	2331	2332	2333	2334	2335	2336	2337	2338	2339	2340	2341	2342	2343	2344	2345	2346	2347	2348	2349	2350	2351	2352	2353	2354	2355	2356	2357	2358	2359	2360	2361	2362	2363	2364	2365	2366	2367	2368	2369	2370	2371	2372	2373	2374	2375	2376	2377	2378	2379	2380	2381	2382	2383	2384	2385	2386	2387	2388	2389	2390	2391	2392	2393	2394	2395	2396	2397	2398	2399	2400	2401	2402	2403	2404	2405	2406	2407	2408	2409	2410	2411	2412	2413	2414	2415	2416	2417	2418	2419	2420	2421	2422	2423	2424	2425	2426	2427	2428	2429	2430	2431	2432	2
--	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	---

10
15
20
25

30

35

In the conventional art, to prevent the "image sticking phenomenon", a layer structure controlling voltage waveform circuit was provided separately from the display driving circuit so as to apply a layer structure controlling voltage waveform to the liquid crystal panel. The layer structure controlling voltage waveform is applied to the liquid crystal in order to cause the layer structure of the antiferroelectric liquid crystal to change from the chevron structure, for example, shown in

Figure 4(a) or 4(c), to the bookshelf structure shown in Figure 4(b). A rectangular wave is suitable for use as the layer structure controlling voltage waveform. It has also been found that a frequency within the range of 1 Hz to 100 Hz and a voltage value within the range of ± 10 V to ± 50 V, where dielectric breakdown does not occur between the top and bottom glass substrates of the liquid crystal panel, are suitable.

Figure 7 shows an example of the layer structure controlling voltage waveform. In the case of the waveform shown, the frequency is 20 Hz and the voltage value is ± 40 V.

On the other hand, the frequency of the display driving voltage waveform for an antiferroelectric liquid crystal, such as shown in Figure 3, is 30 Hz to 70 Hz, though it depends on the display panel used. The voltage applied during the selection period (Se) is, for example, ± 30 V, and the holding voltage applied during the non-selection period (NSe) is usually around ± 10 V.

After studying the above two kinds of voltage waveforms, the inventor has discovered that if the display driving voltage waveform for antiferroelectric liquid crystal is set so that the peak value of the scanning voltage applied during the non-selection period (NSe) becomes equal to the peak value of the voltage applied during the selection period (Se), a voltage waveform close to the optimum layer structure controlling voltage waveform can be obtained.

Figure 8 shows waveforms when the display driving voltage waveform for antiferroelectric liquid crystal shown in Figure 3 is set so that the peak value of the scanning voltage applied during the non-selection period (NSe) becomes equal to the peak value of the voltage applied during the selection period (Se). In Figure 8, (a) is the scanning voltage waveform, (b) is the signal

Sub
a-7
A

voltage waveform, (c) is the composite voltage waveform, and (d) is the light transmittance. The waveform (a) shown in Figure 8 provides a voltage waveform close to the layer structure controlling voltage waveform.

5 The waveform shown in Figure 8 has a reset period (R_s). However, if the peak value of the scanning voltage waveform is made the same for all periods (selection period, non-selection period, and reset period) within one frame, a more effective layer structure controlling
10 voltage waveform can be produced. In view of this, the length of the reset period is made adjustable in the voltage waveform shown in Figure 8. Figure 9 shows the waveform when the reset period (R_s) is set to 0. The driving voltage waveform control circuit 11 shown in
15 Figure 10 controls the scanning voltage waveform generating circuit 13 to control the reset period.

Figure 10 shows a block diagram of the
antiferroelectric liquid crystal display of the present invention having a configuration capable of outputting
20 the layer structure controlling voltage waveform without the need to provide a separate layer structure controlling voltage waveform circuit.

The antiferroelectric liquid crystal display of the present invention comprises, as shown in Figure 10, a
25 liquid crystal panel 10, driving voltage waveform control circuit 11 for controlling the driving voltage waveform, display data generating circuit 12, scanning voltage waveform generating circuit 13, signal voltage waveform generating circuit 14, power supply circuit 15, and
30 temperature sensor 16. The power supply circuit 15 creates a DC voltage necessary for the generation of the scanning voltage waveform and signal voltage waveform, and voltages at necessary levels are output at appropriate timing from the scanning voltage waveform
35 generating circuit 13 and signal voltage waveform generating circuit 14 for application to the liquid crystal panel. These circuits constitute the display

driving circuit.

The DC voltage created by the power supply circuit 15 has seven levels, that is, $\pm V_S$, $\pm V_O$, and 0 that the scanning voltage waveform generating circuit outputs during the selection period, non-selection period, and reset period, respectively, and $\pm V_C$ that the signal voltage waveform generating circuit outputs.

Figure 11 is a diagram showing the configuration of the power supply circuit 15, illustrating an example of the configuration for switching, in accordance with the present invention, the voltage level between $\pm V_S$, which is output from the scanning voltage waveform generating circuit during the selection period, and $\pm V_O$, which is output in the non-selection period.

When outputting the scanning voltage waveform shown in Figure 3(a) for normal liquid crystal driving, selector switches SW1 and SW2 in the power supply circuit 15 shown in Figure 11 are both connected to contacts b. As a result, $\pm V_S$ is output during the selection period and $\pm V_O$ during the non-selection period.

On the other hand, when applying the layer structure controlling voltage waveform, the selector switches SW1 and SW2 in the power supply circuit 15 shown in Figure 11 are both thrown to contacts a. Then, $\pm V_S$ is output during the non-selection period as well as the selection period, thus outputting the scanning voltage waveform shown in Figure 8(a).

In the power supply circuit 15, an AC-DC conversion circuit converts an ordinary AC voltage to a prescribed DC voltage (for example, 5 V). The AC-DC converted voltage is further converted by a DC voltage conversion circuit to create, for example, a DC voltage of about ± 30 V as the selection voltage (V_S), a DC voltage of about ± 7 V as the non-selection voltage (V_O), and a DC voltage of

about ± 6 V as the signal voltage (VC).

As shown in Figure 10, the temperature sensor 16 for measuring the surface temperature of the liquid crystal panel 10 is attached to the surface of the liquid crystal panel 10. Information from this temperature sensor 16 is input to the power supply circuit 15, and the contacts a or b of the switches SW1 and SW2 are selected depending on the temperature change detected.

In the present invention, normally the driving waveform shown in Figure 3 is applied to the liquid crystal to produce the display. On the other hand, when, for example, the temperature of the liquid crystal panel 10 drops from room temperature to a temperature lower than 10°C and then rises above 10°C , the layer structure changes and the "image sticking phenomenon" occurs. In such a case, the layer structure controlling voltage waveform shown in Figure 8 is applied to the liquid crystal panel to alleviate the "image sticking phenomenon".

Figure 12 shows the scanning voltage waveform for the case when a temperature change occurs during application of the normal driving waveform and the contacts of the switches SW1 and SW2 of Figure 11 are switched from b to a to alleviate the "image sticking phenomenon" occurring due to the temperature change. As shown, the normal driving voltage waveform (in frames F1 to F4) is followed by the scanning voltage waveform (from frame F5 onward) of Figure 8(a) which is applied as the layer structure controlling voltage waveform to the liquid crystal. Using a scanning voltage waveform whose one frame period (the sum of the reset period, selection period, and non-selection period) is about 17 ms, a layer structure controlling voltage waveform, in which the peak value of the scanning voltage waveform applied during the selection period and the peak value of the scanning voltage waveform applied during the non-selection period

were both set to ± 30 V, was applied to the liquid crystal for about one second. As a result, the change in the geometry of the layer structure due to the temperature change was corrected, and the "image sticking phenomenon" did not occur. Further, the application of the layer structure controlling voltage waveform had little effect on the display quality, since the application time was very short. The length of time over which the layer structure controlling voltage waveform is applied is determined by issuing an instruction from the driving voltage waveform control circuit 11 to the power supply circuit 15 in Figure 11.

Next, a voltage waveform, similar to the one shown in Figure 9, in which the peak value of the scanning voltage waveform applied during the selection period and the peak value of the scanning voltage waveform applied during the non-selection period were both set to ± 30 V and the reset period was set to 0, was applied as the layer structure controlling voltage waveform. In this case also, the "image sticking phenomenon" could likewise be reduced.

In the above description, the layer structure controlling voltage waveform is output based on the information from the temperature sensor 16, but the layer structure controlling voltage waveform may be output at predetermined intervals of time. In the latter case, the temperature sensor shown in Figure 10 is not needed. Instead, a timer is provided in the power supply circuit 15 so that the layer structure controlling voltage waveform can be output at predetermined intervals of time.

Figure 13 is a diagram showing an example of the structure of the liquid crystal panel 10 constituting the antiferroelectric liquid crystal display used in the present invention. The liquid crystal panel 10 comprises: a pair of glass substrates 21a and 21b between

which an antiferroelectric liquid crystal layer 20 with a thickness of about 2 μm is sandwiched; and sealing members 22a and 22b for bonding the two glass substrates together. On the opposing surfaces of the glass substrates are formed electrodes 23a and 23b, which are coated with polymeric alignment films 24a and 24b, respectively, and are treated by rubbing. On the outside surface of one glass substrate is disposed a first polarizer 25a with its polarization axis oriented parallel to the rubbing axis, while on the outside surface of the other glass substrate, a second polarizer 25b is arranged with its polarization axis oriented at 90° to the polarization axis of the first polarizer 25a. The temperature sensor 16 is mounted on the surface of the liquid crystal panel 10.

105
29
4